

TITLE: Autonomous Portable Communication Network

BACKGROUND OF THE INVENTION

5 FIELD OF THE INVENTION:

The present invention relates to portable communications networks and systems, and more particularly to such a network where individual units are enabled for direct communication with each other and for acting as automatic repeaters for other units in communication.

10 DESCRIPTION OF RELATED ART:

The following art defines the present state of this field:

15 The existing cellular telephone system requires three separate units: multiple mobile cellular phones, multiple cell-sites and a single telephone switching office. The mobile cellular phones are free to move wherever they wish among the various fixed cell-sites. Communication between the mobile units and the cell-sites are via a two-way RF communication data link. The cell-site closest the mobile unit provides the communications with the overall cellular system.

20

The telephone switching office is connected to all of the cell-sites by either a high-speed telephone wire line or by a fixed microwave data link. Control of all internal switching of calls is provided by the mobile telephone switching office. The telephone switching office also provides the coordination of all switching functions. This includes the connections of
25 the cellular system to the nation-wide wire line telephone network.

Each cell-site manages data communication between the mobile units and the mobile telephone switching office. A single cell-site covers a particular geographical area and has the ability to provide a rough location of each mobile unit within its area.

- 5 A simple, low cost mobile unit that can incorporate all of the functions of the expensive cell-sites and telephone switching offices is highly desirable.

10 The prior art teaches the use of portable two-way radio communication but does not teach an automated network of portable units programmed to act as repeater stations as well as personal communicators in establishing a range of communications possibilities much greater than the range of individual units. The present invention fulfills these needs and provides further related advantages as described in the following summary.

SUMMARY OF THE INVENTION

15 The present invention teaches certain benefits in construction and use which give rise to the objectives described below.

20 A system of individual portable RF units that structure their own network. A unit may or may not interconnect to other multi-media networks for communications and location between RF unit-members and non-unit-members. Each unit has an "inherent-mode" and an "external-mode" for routing and forwarding calls not addressed to it. An "inherent-mode" enables a unit to operate when not connected to another media network and routes information only within the RF network. An "external-mode" enables a unit to operate
25 when connected to another media network. This enables information to be routed inside and outside the RF network, providing seamless integration between the RF network and various multi-media networks. Also, the "external-mode" provide the means for the RF network and the connected network to relieve each others' congestion or failure. In addition, each unit has as a "fixed-mode" and "remote-mode" of operation. A "fixed-mode" is initiated when a

unit is connected to a specific geographical location. Otherwise the unit operates in the "remote-mode". In the "fixed-mode", units have an earth's position of latitude, longitude and altitude available for transfer to other's unit. This enables any unit to determine its relative position within the network by means of triangulation to several units' specific geographical locations and maintain an accurate earth's position.

Other features and advantages of the present invention will become apparent from the following more detailed description, taken in conjunction with the accompanying drawings, which illustrate, by way of example, the principles of the invention.

BRIEF DESCRIPTION OF THE DRAWINGS

The accompanying drawings illustrate the present invention. In such drawings:

FIG. 1 is an external view of one communications unit of the invention;

FIG. 2 is a geographical plan view of an example of an arrangement of six of the communications units in network communication;

FIG. 3 is an electronic block diagram of a preferred example of an electronic embodiment of the portable RF unit for network use in accordance with this invention.

FIG. 4 is an electronic block diagram of a preferred example of an electronic embodiment of the data processing section of the portable RF unit for network use in accordance with this invention.

FIG. 5 is the various data formats for messages transferred between units within the preferred embodiment of the portable RF unit for network use in accordance with this invention.

DETAILED DESCRIPTION OF THE INVENTION

The above described drawing figures illustrate the invention in at least one of its preferred
5 embodiments, which is further defined in detail in the following description.

Fig. 1 shows external features of one of the portable communication units of the present
invention. Unit 10 is typical of a plurality of identical units. It is preferably the size of a
hand-held device and configured in size so that it can be positioned adjacent to both the
10 mouth and the ear so that microphone 12 may pick up speech and other sounds, while
speaker 14 delivers sound to the user's ear. The housing 16 of the unit 10 may have a
plurality of key inputs, such as twelve key input buttons 18 and may have a series of function
buttons 20. The housing contains a two-way communications means such as a radio, and
thus has an antenna 22 for wave energy coupling. While the unit 10 contains batteries and is
15 preferably hand-portable, it may also be provided with a power input jack 24 for
supplemental power input for battery charging and/or for powering the electronics in the unit
when the unit is positioned near an external power supply. In addition, the unit has data
input and output jacks 26 and 28 for the transmission (TX) and receiving (RX) of data other
than purely audio data. A standard telephone land line connection 28A is provided to allow
20 communication via a standard telephone network.

Fig. 2 shows unit 10 as a first unit in a network. The second unit is shown at 30; the third
unit is shown at 32; the fourth unit is shown at 34; the fifth unit is shown at 36; and the sixth
unit is shown at 38. The distribution of the units in Fig. 2 is an example of the manner in
25 which they may be distributed with respect to each other during use. It is merely an example
to illustrate the different modes of operation. Each of the units has a maximum radius of
useful range. The dashed line arcs indicate the useful range or radius of each of the units and
illustrates how the network ranges overlap. Each of the units has a unique address with
respect to other units in the network.

Referring to Fig. 3, we show a block diagram of a two-way radio generally indicated at 40. The radio 40 is comprised of a transmitter 42 and a receiver 44. The radio may be of any of the standard types such as AM, FM, Bluetooth, etc., using any of the various modulation schemes (CDMA, TDMA, etc.). Generally, the present invention covers any signaling means using wave energy. Incoming RF signals are received on antenna 22 and passed to the receiver 44. The receiver separates the signal from the RF carrier and outputs the analog signal 60. This signal is converted to a digital signal via the analog to digital converter 62 and passed this digital signal 79 to the signal analyzer 64 for processing by digital means. The signal analyzer section 64 will be described in more detail below.

As indicated, the signal analyzer section 64 operates in a digital mode so that output signals are output through digital-to-analog converter 66 to line 68. The line 68 is in analog form and serves as the input to transmitter 42. The transmitter 42 generates an RF signal and outputs it to the antenna 22. The signal is thereby transmitted to all receivers in range that receive that frequency.

The signal analyzer 64 outputs data for the display 72 on line 46, the speaker 14 on line 72 and data for external equipment on line 70 to an output connector. Input data enters the signal analyzer either from a keyboard 74, microphone 12 on line 78 or from an input connector on line 56.

The detail description for the signal analyzer section 64 is shown in Fig. 4. The signal analyzer reads and decodes the label on the incoming RF messages and acts accordingly. Each unit within the network (see Fig. 2) has a unique address so that other members of the network can reach the proper destination.

Case I. Repeat Message Not Required

For example, the unit 10, as seen in Fig. 3, has a radius R_1 which reaches units 34, 30 and 38. If the source of the signal is unit 38 and its destination is unit 10, the compare transmit received address for this unit address 80 in unit 10, shown in Fig. 2, determines that the signal is local and sends the signal through line 82 to decode message label 84. Since the routing is direct from unit 38 to unit 10, no special route is required. The decode message label 84 determines which of the following messages is received; call initiate, reply data or broadcast. If a call initiate is decoded (shown in Fig. 5A or 5B) the signal is output on line 85 to generate a reply message 86. The generate reply message 86 forms a reply message as shown in Fig. 5G. the reply message is output on line 93 and sent to the digital-to-analog converter 66. If a reply message is decoded (shown in Fig. 5G) the output is on line 87. The save TX address from message 88 saves this part of the received address so it can be attached to future transmissions onto the network. The reply received line 84 indicates to the output device 98 that a connection has been achieved and communication can begin. If a data message is decoded (shown in Fig. 5D) the output is on line 89. The save TX address from message and strip off data from message 90 outputs data to the output device 98 for output to the appropriate device. The saved TX address is saved so it can be attached to future transmissions onto the network. If a broadcast message is decoded (shown in Fig. 5E) the output appears on line 91. The strip-off broadcast data and re-transmit 92 from message and strip-off data from message 90 outputs data to the output device 98 for output to the appropriate device. The saved transmission address is saved so it can be attached to future transmissions through the network.

Case II. Repeat Message Required

If the source of the transmitted signal is unit 32 (Fig. 2) and the destination is unit 10, the direct signal from unit 32 only reaches out to the radius R_3 that does not directly reach unit 10. Instead, units 34 and 36 pick up the signal. When the signal arrives, it is compared with the transmit received address for this unit; address 80, it is indicated that the message is for another unit (line 90). The message on line 90 goes to decode message the label and test

FEC 100. The decoded messages are call initiate (ALL), call initiate (FIXED), reply and data. If a call initiate (ALL) is decoded (shown in FIG. 5B) the signal is output on line 101 to replace TX address in message with this unit address 104. The replace TX address in message with this unit address 104 forms a reply message as shown in FIG. 5C. The reply message is output on line 105 and sent to save message called address and receiver address 106. The two addresses are saved so they will be available if needed for return path communication. The reply message is passed on line 107 to select random delay time before re-transmit 108. After the random time delay the transmission signal is output on line 93. This signal is sent to the digital to analog converter 66. If a call initiate (FIXED) is decoded (shown in FIG. 5A) the signal is output on line 102. If this unit is in a fixed location, the close switch, if unit is a fixed unit 103 will close the switch in line 102 and send the signal to replace the TX address in the message with this unit address 104. If the unit is not in a fixed location, the switch will be open and the message will be ignored. If the switch is closed the processing will be the same as call initiate (ALL).

If reply and data messages are decoded (shown in FIG. 5G) the output is on line 109 for reply and line 110 for data. The test for this units address in the TX section of the message 111 will look for the message and will ignore the message if it is not present. If the address is present the reply signal will be output on line 112. The saved message from above is compared with caller and receiver addresses until one is found that agrees with this message caller and then the receiver uses the TX address from the save message to replace the TX address of the message 113. After this operation is completed the modified, the message is output on line 93.

Case III. Output Data From Input Source

Data generated within the unit from either voice or digital data input into input device 114 has two outputs. Call initiate line 115 or data line 116. The call initiate signal goes to generate call initiate message 117 and it forms a call initiate message as shown in FIG. 5B

on line 93. A data message output on line 116 goes to generate data message 118. A data message format as shown in FIG. 5D is formed and output on line 93. While it is convenient for all of the units to be portable, of course there is the battery power limitation. In a network where at least one of the units can be less portable, it may be located in an office trailer or in a vehicle to operate from local power. Such are considered to be fixed units because of their larger power supply, which does not permit them to be hand-portable. Furthermore, such fixed units can be connected to telephone lines or other fairly fixed data sources and outputs should such be helpful. Also, the fixed units may be accurately located with respect to latitude and longitude should such be helpful for the task at hand.

A "call initiate" message is formed by putting a label to define the message type followed by the address of the unit initiating the call, the address of the destination unit and the address of the unit transmitting the message. Two types of call initiate messages may generated. Always the first message will be directed to fixed units. An attempt will be made to communicate with other members of the network by using only fixed units. This is done to save the remote unit's battery power. If after a period of time, i.e., approximately, one second, a reply is not received from the addressed unit, the second type of call initiate will be sent. This message is the same as the first but with the label changed. The second type message will allow all units (fixed and remote) to respond to the call initiate message. Each unit receiving the "call initiate" message will examine the label on the call initiate message to determine the type of call initiate. A remote unit will ignore the message if it is for fixed units only. If it is a message of the second type, then all units will respond.

When a unit receives a call initiate message and it determines it should respond, it examines the destination address and compares it with its own. If this address section of the message agrees with the address of this unit, it will accept the message and respond as appropriate. If the destination address is for another unit, this unit will act as a repeater for "call initiate" messages addressed to other members of the network. When this occurs, the message will be saved as it is received so that the address information can be used to route reply messages

back to the originator. Once the "call initiate" message has been saved, the unit forms a new message by replacing the transmitting address in the message with its own address. The modified message is then retransmitted onto the network. By this method, the message will eventually reach the destination unit. There will be multiple modified messages transmitted throughout the network. The first message reaching the destination will be designated as the path for this communication.

A "call reply" message will be transmitted by the destination unit to indicate that the communication can take place. The address information attached to the "call initiate" messages during the forward transmission will be used to route the reply back to the originating unit. This will establish the data path for further transfer of multimedia data. The repeating function by any unit occurs without its user's knowledge. In the event the user wishes to use his unit while it is being a part of a communication loop, an alternate path has to be established for continuing the data transfer. The initiating call unit will perform a background computation during a communication to establish an alternate path for communication in the event the current path is broken. The alternate path will switch into the loop if at any time the signal becomes too weak or the path interrupted. The alternate path is established by issuing a call initiate message synchronized and time delayed relative to the normal communication message in the primary established path. If an alternate path is not available and the owner wants to use his unit, he will get a busy signal until the existing transmission has completed. If an alternate path is not available and the signal becomes too weak, then the communication loop will be automatically broken.

An example of this communication scheme is shown in the figures. Assume unit 32 wishes to communicate with unit 38 and that the transmission range of unit 32 can only reach units numbers 34 and 36. The call initiate message transmitted by unit 32 is: fixed label, address 32, address 38, address 32. This message indicates that it is a message that is to be responded to by fixed units only. It also indicates that the message is sent by unit 32 to

destination unit 38. The fourth element in the message indicates the unit transmitting the message is unit 32.

Assume all units are fixed units at this point. When units numbers 34 and 36 receive this message they examine the label and see they must respond. They then examine the destination address and compare it to their own. Since the destination address is unit 38, this will not agree with their address and they will be required to retransmit the message. Each unit (34 and 36) will save the message they receive from unit 32 and then modify the message before retransmitting. They modify the message by changing the fourth part of the message. Unit 34 changes the message by putting its address in the fourth part of the message. Unit 36 puts its address in the fourth part of the message. Both units retransmit the message with their address in the fourth position.

Unit 34 has a transmission range which reaches back to unit 32 and forward to units numbers 36, 10 and 30. Unit 36 has a range to reach units 32, 34 and 30. When units 32, 34 and 36 receive these new messages, they compare them with the message they have stored and see that is the same with the exception of the fourth field in the message. Each unit, therefore, ignores the message. When unit number 10 receives the message from unit number 34, it will perform the same examination on the message as that described for unit 34. It will store the message as received, replace the fourth field of the message with its address and retransmit. Unit 30 will receive messages from both units 34 and 36. It will perform the same functions on the first message to arrive as described for unit 10. When the second message arrives, it will be ignored since unit 30 has already saved the message with only the fourth field changed. Unit 34 will receive and ignore the message from number 10 and number 30. Unit 36 will receive and ignore the message from unit 30. The messages from units numbers 10 and 30 will both be received by unit 38. The first one arriving at unit 38 will be utilized, and the second one will be rejected. If two signals arrive at one of the units at the same time, both will be rejected and the unit will await the receipt of a clear message, i.e., no interference.

Unit 38 will examine the message and see that it is the addressee. It will respond by generating a "call reply." The "call reply" message is similar to the call initiate message with only the label changed. The fourth field of the call reply message will be the unit address of the unit that is to reply. For example, let's assume that the path for the communication between unit 32 and number 38 is 32 to 34, 34 to 30 and 30 to 38. Unit 38 will reply with the message of: Call reply format, unit initiating the call address, unit destination address, and unit address for repeating the message. In this case, unit 38 will reply with: call reply label, 32, 38, 30. When unit 30 receives this message, it will see this is a call reply message that has its address in the fourth field. It will then change the fourth field to the value 34 and retransmit the message. The value 34 is obtained from the message it received and saved from the call initiate message. When unit 10 receives the message from unit 38, it will note that its address is not in the fourth field and will therefore ignore it. Unit 34 will receive the message from unit 30 and will replace the fourth field with a 32 and retransmit the call reply message thereby establishing the communication path.

Unit 32 will transmit a message that has the following format: "message" label, originating address, destination address, repeater address and message content. The repeater address will be 34. Unit number will receive this message and change the repeater address to 30 and retransmit. Unit 30 will receive this message and change the repeater address to 38 before retransmitting. All units receiving the message that does not have its address in the repeater field will ignore the message.

Communications within the network can only occur within a local area. A local area is defined as the area that has direct communication between adjacent members. Once the distance gets too great, the direct and repeat capabilities are lost. To get around this limitation, interface with other multimedia equipment is provided using the unit. For example, the signals may be routed on public telephone lines for some distance to get to another local area of the system. Once the signal gets into the second local area of the

system, it can be brought out into the network using any unit and then be propagated throughout the new local area. Multimedia equipment that provides communication paths other than the telephone can be used to bridge gaps within the system. Interface to other multimedia equipment provides communications worldwide with non-network members.

5 The unit provides a terminal to access, control, route and transfer data throughout the network and over any selected multimedia equipment. Network members within a local area communicate with one another using an RF data link. No interface with any land line is required.

10 The various portable units and the network are useful in both communication and identification of location between points.

As a portable voice communication network, the input device 12 is a microphone that is energized by a user's voice. The output device 14 is a speaker to translate the signals into
15 audio signals. A number of other different kinds of input devices and output devices are possible and should be considered included within the scope of the invention. The signal analysis section 64 can either use the data locally or pass it on to other units or multimedia. In addition data processing may compress the data before storing the information in memory or transmitting it to other multimedia. Data received from other units or multimedia may
20 require data processing to either store the data in memory or to decompress the information before sending it to external equipment.

The output connection 70 and input connection 56 provides the hardware interface for connecting to various systems. This could be a computer interfacing with a computer
25 network such as the Internet. Both serial and parallel data transfer to and from computers may be used. A Keyboard may be the input device to provide the means for the operator to enter information into the unit. The data entry may be for control of the system or may be data that is to be stored within, transmitted via one of the multimedia channels or transmitted

via the wave energy link. Signal analysis section 64 reads the keyboard inputs and interprets the commands and utilizes the keystrokes for generating messages and/or data.

5 An output display as an output device provides the operator with information needed for operating the system, displaying messages to be sent and/or received. Signal analysis section 64 performs all the formatting of information and control needed to generate the display. An image interface as an input device is the hardware needed to accept image information from any image reading equipment and convert it into a digital signal for storage and/or transmission to another location via the RF link or other multimedia channel. The image
10 interface also converts data for outputting to image display equipment. Signal analysis section 64 can transmit and/or store the data as it is received from the image equipment or may compress it prior to transmission or storage. Image data, being output for a display, will be decompressed by data processing if necessary. This includes data which is stored within the unit and data received over any of the multimedia channels.

15 The Memory, as an input device provides storage of phone numbers, E-mail messages, paging messages, voice-mail, etc. for retrieval by the operator. The data for storage may be generated by the operator or may come to the unit via RF or one of the multimedia channels. The storage in the memory is nonvolatile so that the stored information is not lost if power to
20 the unit is interrupted. Signal analysis section 64 controls the routing of data being stored and retrieval of data from memory. The operator may view any of these data on the display. The operator may also modify and/or erase any of these stored data.

25 Another feature is the provision of adding position (latitude, longitude and altitude) data to the location where the telephone connection is made. When the telephone connection is made, the actual location of the unit is fixed. The position of this unit can be transmitted to remote units so they may compute their positions via triangulation from multiple units within the network. Range for triangulation computation is obtained from one unit to another by timing the turnaround time between sending a message to another unit and

receiving a reply from that unit. The position in latitude and longitude of the interrogated unit is listed in the reply message and includes any fixed time delay within the responding unit. The data message format, as shown in Fig. 5D, is used for the request for range and reply from another unit. Repeated range interrogation is performed every few seconds so
5 that the position of the unit is updated as it moves relative to the surface of the Earth. .

While the invention has been described with reference to at least one preferred embodiment, it is to be clearly understood by those skilled in the art that the invention is not limited thereto. Rather, the scope of the invention is to be interpreted only in conjunction with the
10 appended claims.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206